

电阻互换精度: R25 = 10.0K $\Omega$   $\pm$ 1.0%

B25-50 = 3470K $\pm$ 1.0%

-15	56.52811	27	9.26532	69	2.23561	111	0.71289
-14	53.84483	28	8.92138	70	2.16934	112	0.69567
-13	51.30006	29	8.59214	71	2.10529	113	0.67893
-12	48.89091	30	8.2765	72	2.04352	114	0.66266
-11	46.61393	31	7.97489	73	1.98383	115	0.64688
-10	44.45071	32	7.68523	74	1.92615	116	0.63155
-9	42.40323	33	7.40786	75	1.87046	117	0.61662
-8	40.46144	34	7.14175	76	1.81664	118	0.60214
-7	38.61851	35	6.88675	77	1.76461	119	0.58804
-6	36.87093	36	6.64228	78	1.71437	120	0.57435
-5	35.21336	37	6.40773	79	1.66572	121	0.56103
-4	33.63958	38	6.18252	80	1.61873	122	0.5481
-3	32.145	39	5.96687	81	1.57336	123	0.53551
-2	30.72636	40	5.75952	82	1.52944	124	0.52326
-1	29.37686	41	5.56034	83	1.48691	125	0.51135
0	28.09507	42	5.36935	84	1.44581	126	0.49978
1	26.87578	43	5.18572	85	1.40604	127	0.4885
2	25.71604	44	5.00957	86	1.36751	128	0.47754
3	24.61529	45	4.84002	87	1.33026	129	0.46687
4	23.56596	46	4.67741	88	1.29424	130	0.45647
5	22.56719	47	4.52076	89	1.25933	131	0.44637
6	21.61787	48	4.37045	90	1.2255	132	0.43652
7	20.712	49	4.22581	91	1.19275	133	0.42694
8	19.84957	50	4.08679	92	1.16103	134	0.41762
9	19.02895	51	3.95289	93	1.13035	135	0.40853
10	18.2458	52	3.82424	94	1.10059	136	0.39968
11	17.49982	53	3.70016	95	1.07177	137	0.39106
12	16.78812	54	3.58099	96	1.04383	138	0.38267
13	16.10902	55	3.46615	97	1.01674	139	0.37449
14	15.46159	56	3.35563	98	0.99046	140	0.36652
15	14.84353	57	3.24919	99	0.96501	141	0.35876
16	14.25457	58	3.14666	100	0.94032	142	0.35118
17	13.69047	59	3.04785	101	0.91641	143	0.34381
18	13.15309	60	2.95273	102	0.8932	144	0.33663
19	12.63985	61	2.86098	103	0.87065	145	0.32963
20	12.14869	62	2.77252	104	0.84883	146	0.32279
21	11.67926	63	2.68719	105	0.82763	147	0.31613
22	11.2311	64	2.60499	106	0.80705	148	0.30964
23	10.80245	65	2.52578	107	0.78707	149	0.30331
24	10.39251	66	2.44927	108	0.76769	150	0.29713
25	9.99986	67	2.37553	109	0.74888		
26	9.62434	68	2.30434	110	0.73063		